

## Description

The Keypad Model XMB611 is a battery operated, wireless alphanumeric keypad/badge reader combination device designed for programming and operating VIDEOFIED™ security systems.

The keypad features a two line, 16 character liquid crystal (LCD) display, multi-function push buttons, panic assistance, built-in sounder, and S2View® spread spectrum encrypted wireless circuitry for secure 915MHz two-way communication with the control panel.

The LCD backlight turns off automatically after 30 seconds of keypad inactivity to conserve battery power. Pressing a button or presenting a badge will turn the backlight on.

The keypad can be used to program and configure Videofied™ security systems. S2View® spread spectrum encrypted wireless circuitry effectively makes the keypad a mobile programmer that can be used anywhere within the installation site during system programming. Because the keypad is a supervised device, once programming is completed the keypad must be permanently mounted or deleted from the system. The easy to understand display guides you through programming, prompting you for simple yes/no or data entry responses. The left and right arrow buttons cycle through menus or values until the desired option is displayed. Text entries are done using the 0 - 9 buttons and can be in lowercase, uppercase, or a combination of both. Complete punctuation symbols are also available for data entries such as website/IP addresses and component location naming.

The keypad is typically installed near entry/exit doors to allow system users enough time to arm and exit the premises, and to enter and disarm the system before time delay expires. When the system is armed, the built-in sounder emits a series of exit delay beeps to remind the user to exit before the beeps stop. Upon entering the armed premises, the built-in sounder emits entry delay beeps to remind the user to disarm the system to avoid an alarm. A dual tamper function provides detection for both keypad cover and wall tamper.

The keypad is powered by three or four lithium batteries that can last up to four years or more, depending on the amount of keypad activity. The keypad transmits a check-in signal every eight minutes that includes its unique identification code, along with the tamper condition, serial number, date of manufacture, software revision and battery status. Videofied alarm systems support up to three keypads per system.

## Features

- > S2View® - Spread Spectrum, VIDEOFIED™, Interactive AES Encrypted Wireless technology provides optimum signal integrity and security.
- > Mobility - program the system from anywhere on site.
- > Display - Two line, 16 character display with automatic backlight. 30 second backlight timer to conserve battery power.
- > Buttons - complete alphanumeric setting/parameter entries in programming mode; standard and custom operation in normal operating mode.
- > Built-in sounder - provides entry/exit delay beeps and alarm sounds.
- > Panic Assistance - for manual activation anytime.
- > Supervised - transmits a check-in/status signal every 8 minutes indicating tamper state, serial number, date of manufacture, software revision and battery status.
- > Dual tamper - provides detection for both wall and cover.



### Electrical Data

Panel Compatibility Videofied Alarm Panel XL,XT,XTIP, V6000

#### Power requirements:

Type: 3.6v SAFT Lithium, LS14500, AA Batteries Only

Nominal Voltage: 3.6v

Low Voltage Limit:

2.1v - LCD will stop functioning but communication is working

3.0v - LCD will function and communication is working

Quantity 3x or 4x

Battery life (estimated) Up to 4 years

#### RF technology:

2 way S<sup>2</sup>View© RSI Technologies

915MHz frequency hopping

Radio type Spread Spectrum Bidirectional RF

Operating frequency 915 MHz

Transmission security AES algorithm encryption

Supervision Panel polls devices every 8 minutes

Antenna Integrated

Tamper detection Wall and cover tampered

#### Keypad:

Keys: 23x Keys

Allowed Time for Code Entry: 60s

Number of Illegal codes: 186 (depending on panel features)

User code input attempts before lockout: 5

Lockout duration: 90 seconds

Memory Lifetime: No Limit (Flash Memory)

Assistance Request Police/Medical/Fire

Display type Liquid-crystal (LCD)

Display size Two lines, 16 characters each

Display backlighting Automatic

#### Badge Reader:

Format: ISO/IEC 14443A

Type: MiFare 13.56MHz 1K/4K

#### Built-in sounder:

Piezo Buzzer: Emits entry/exit delay beeps, alarms

Panic button One (Must be programmed/Enabled)

Operating temperature 14° - +104° F (-10° - +40° C)

Maximum relative humidity 75%, non-condensing

### Physical Data

Material ABS UL94-V0

Dimensions (LxWxD): 6.3 x 3.6 x 1.2 Inches  
(160 x 92 x 31 mm)

Weight 6.35oz (180gr) without batteries

### Installation/Mounting

Wall Mount 3 Screws (including one for the tamper)

Case Lock Mechanical lock and optional screw

### Certification & Approvals

USA FCC Part 15C  
UL1023 (Applied For)

Canada RSS210

## FCC Regulatory Information for USA and CANADA

FCC Part 15.21 Changes or modifications made to this equipment not expressly approved by RSI VideoTechnologies may void the FCC authorization to operate this equipment.

### FCC Part 15.105 Class B

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

### Radio frequency radiation exposure information according 2.1091 / 2.1093 / OET bulletin 65

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance of 20 cm between the radiator and your body.

This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

This device complies with Part 15 of the FCC Rules and with RSS-210 of Industry Canada.

Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.



**EMEA SALES**  
23, avenue du Général Leclerc  
92340 BOURG-LA-REINE  
FRANCE  
Hotline: +33 (0)820 846 620  
Fax: +33 (0)1 82 69 80 10

**USA SALES**  
1375 Willow Lake Blvd. #103  
Vadnais Heights, MN 55110  
USA  
Hotline: +1 877 206 5800  
Fax: +1 651 762 4693

[www.videofied.com](http://www.videofied.com)

© 2011 RSI VIDEO TECHNOLOGIES. VIDEOFIED® is a Registered Trademark of RSI VIDEO TECHNOLOGIES.  
S'View® is a registered trademark of RSI VIDEO TECHNOLOGIES. Specifications subject to change without notice.